FLN 30/15 - no longer available




Applications

As a mains transformer for adjustment of the voltage and simple electrical

As an isolating transformer for the safe electrical isolation of the input and output sides. The transformer may be used to set up protective separation as a protective measure.

As a safety isolating transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Sample application



Picture shows FLN 30/12

Standards

Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6, UL 5085-1/-2, CSA 22.2 No.66

Approvals







ENEC 10 (VDE), UL 5085-1/-2, CSA 22.2 No.66





Safety isolating transformer **FLN 30/15 - no longer available**

	Туре	FLN 30/15 - no longer		Type
.+ Դ Ը		available	30	_
1+	Input			Terminal and mou
_	Rated input voltage	2 x 115 Vac		Terminals
ate	Rated frequency	50 - 60 Hz	atí	Measures and we
Electrical data	Output		Mechanical data	Core type
ca	Rated output voltage	2 x 15 Vac	- es	Weight
다	Rated Power	30.0 VA		
9	No-load voltage (app. x factor)	1.19	i ii	
Ш	No-load loss (typ.)	2.30 W	<u></u>	
	Efficiency	77.0 %	≥	
	Standards			
	Classification	Safety isolating transformer		
	Approvals			
	Approvals	cURus, ENEC 10 (VDE)		
	Environment			
	Ambient temperature max.	70 °C		
	Safety and protection			
	Туре	Encapsulated		
	Insulation class	В		
	Protection index	IP 00		
	Safety class (prepared)	<u>II</u>		
	Short circuit strength	non-short-circuit proof		
	Catalogue logic			
		Not for new designs		
		Alternative type FL 30/15		
	Order numbers			
	Order Number	FLN 30/15 - no longer available		

