#### Line reactor, three-phase, aluminium LR3A 40-4/90 Discontinued line - not for new designs



## Standards

Line- and commutation reactor to DIN EN 61558-2-20, IEC 61558-2-20, UL 506, CSA 22.2

# Advantages

Use as line reactor, commutating reactor or PFC reactor

Weight reduction through aluminum winding

Ensuring the short-circuit voltage of 3, 4 or 5 % to the mains

Power harmonic damping

Starting current limitation

Increases the service life of consumers

Low ripple

Bridging voltage dips

Peak current limitation

Very good corrosion protection and low noise thanks to vacuum impregnation  $% \left( {{{\rm{D}}_{\rm{s}}}} \right)$ 

Integrated lifting rings

## Applications

Line reactor to minimise mains pollution, to reduce the reactive-power components and charging currents in the DC link capacitor and to improve the cos(phi).



c Sus 🗇

UL 506, CSA 22.2





# Line reactor, three-phase, aluminium LR3A 40-4/90 Discontinued line - not for new designs

Туре	LR3A 40-4/90 Discontinued line - not for new designs	0	Туре		LR3A 40-4/90 Discontinued line - not for new designs
Operating data		30	Terminal and mounting		
Rated voltage	3 x 400 Vac	D	Terminals phase		Flat copper
Rated voltage (IEC)	3 x 690 Vac	data	Terminals PE		for M8
Rated voltage (UL)	3 x 600 Vac		Fixing method		Fixing rail
Short circuit voltage uK	4 % @ 400 Vac	ca	Fixing screws		M8
Rated frequency range high	50 Hz	Mechanical	Measures and weights		
Voltage drop	9.2 Vac	19	Weight		10.95 kg
Rated current	90 A	60			5
Inductance	0.330 mH	≥			~
Inductance deviation	±10 %				
Output					
Power loss	313.6 W			200.0	
Approvals				20010	
Approvals	cURus				79.0
Environment			<b>∠</b> 267.0 ►	<b>4</b> <u>149.0</u> ►	
Ambient temperature	-10 °C to +40 °C			l <b>⊲</b> _0.0 _►	
Type of cooling	AN				<b>↓</b> ↓
Safety and protection					
Туре	Open type				
Protection index	IP 00				
Safety class (prepared)	1				
Insulation class	IEC=H, UL=class 180				
Test voltage	4000 Vac				
Order numbers					
Order Number	LR3A 40-4/90 Discontinued line - not for new designs				

