Motor reactor MR3-AD250-485-0



Standards

Output reactor for frequency converter DIN EN 61558-2-20, IEC 61558-2-20 Advantages

High damping of edge steepness

High damping of inverter switching frequency

Reduction of leakage current at low construction volumes

Long shielded cable lengths possible

High efficiency

Very good corrosion protection and low noise thanks to vacuum impregnation $% \left({{{\left[{{{\rm{N}}} \right]}_{{\rm{N}}}}_{{\rm{N}}}} \right)} \right)$

Applications

Motor reactor for the limitation of the voltage peaks damaging to the motor insulation (dv/dt).





BLOCK Transformatoren-Elektronik GmbH • Phone +49 4231 678-0 • info@block.eu



Motor reactor MR3-AD250-485-0

	Туре	MR3-AD250-485-0		Туре	MR3-AD250-485-0
Electrical data 🖡 🚽	Operating data		0	Terminal and mounting	
	Rated voltage	3 x 480 Vac		Terminals phase	5/16" - Bolt
	Rated current	250 A		Fixing method	Fixing rail
	for motor rated output approx.	149.00 kW	ta	Measures and weights	
	Inductance	0.150 mH	data	Weight	30.9 kg
	Rated frequency	0 - 60 Hz			C C
	Output		.ö		
	Switching frequency	2 – 10 kHz			
	Approvals		Mechanical		
	Approvals	cULus	Σ		
	Environment				
	Ambient temperature	-10 °C – + 50 °C			
	Safety and protection				
	Туре	Open type			
	Protection index	IP 00			
	Test voltage	4000 Vac, 50 Hz			
	Max. temp. rise	135 °C			
	Order numbers				
	Order Number	MR3-AD250-485-0			