## Motor reactor MR3-AD320-483-0



## Standards

Output reactor for frequency converter DIN EN 61558-2-20, IEC 61558-2-20 Advantages

High damping of edge steepness

High damping of inverter switching frequency

Reduction of leakage current at low construction volumes

Long shielded cable lengths possible

High efficiency

Very good corrosion protection and low noise thanks to vacuum impregnation  $% \left( {{{\left[ {{{\rm{N}}} \right]}_{{\rm{N}}}}_{{\rm{N}}}} \right)} \right)$ 

## Applications

Motor reactor for the limitation of the voltage peaks damaging to the motor insulation (dv/dt).





BLOCK Transformatoren-Elektronik GmbH • Phone +49 4231 678-0 • info@block.eu



## Motor reactor MR3-AD320-483-0

Туре	MR3-AD320-483-0	Туре	MR3-AD320-483-0
5 Operating data		E Terminal and mounting	
+ Rated voltage	3 x 480 Vac	Terminals phase	3/8" - Bolt
Rated current	320 A	Fixing method	Fixing rail
g for motor rated output approx.	186.00 kW	🖸 🖸 Measures and weights	
g for motor rated output approx. Inductance	0.070 mH	Measures and weights	44.2 kg
	0 - 60 Hz		5
Rated frequency Output Switching frequency Approvals		ici	
Switching frequency	2 – 10 kHz	Jar	
🖁 🛛 Approvals		Mechanical	
Approvals	cULus	ž	
Environment			
Ambient temperature	-10 °C - + 50 °C		
Safety and protection			
Туре	Open type		
Protection index	IP 00		
Test voltage	4000 Vac, 50 Hz		
Max. temp. rise	135 °C		
Order numbers			
Order Number	MR3-AD320-483-0		

