VCN 50/1/15 - no longer available




Applications

As a mains transformer for adjustment of the voltage and simple electrical

As a safety isolating transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Sample application



Standards

Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6, $\rm IEC$ 6158-2-6, $\rm I$ UL 5085-1/-2, CSA 22.2 No.66

Approvals











Safety isolating transformer

VCN 50/1/15 - no longer available

Туре		VCN 50/1/15 - no longer
1+ Input		available
Input		
Rated input voltage	9	230 Vac
Rated frequency		50 - 60 Hz
Rated Input Voltagii Rated frequency Output Rated output volta Rated Power No-load voltage (ap		
Rated output volta	ge	15.0 Vac
Rated Power		50.0 VA
No-load voltage (app. x factor)		1.13
□ No-load loss (typ.)		4.80 W
Efficiency		84.0 %
Standards		
Classification		Safety isolating transformer
Approvals		
Approvals		cURus, VDE
Environment		
Ambient temperature max.		70 °C
Safety and pro	tection	
Туре		Encapsulated
Insulation class		В
Protection index		IP 00
Safety class (prepa	ired)	II
Short circuit stren	gth	non-short-circuit proof
Order numbers	3	
Order Number		VCN 50/1/15 - no longer available

