Safety isolating transformer

VR 30/2/9



Advantages

Minimum size at high output

Also with double output voltage for series or parallel connection

Permanent corrosion protection, high insulation value and maximum electrical reliability thanks to XtraDenseFill resin encapsulation


Self-extinguishing potting material

Space saving installation thanks to additional screw mounting in the base

Applications

Safety transformer for the safe electrical isolation of the input and output sides. The transformer is suitable for creating SELV and PELV circuits because of the limit on the output voltage.

Sample application



Standards

Safety isolating transformer to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6, UL 5085-1/-2, CSA 22.2 No.66

Approvals







VDE, UL 5085-1/-2, CSA 22.2 No.66





Safety isolating transformer **VR 30/2/9**

Type	VR 30/2/9	Type	VR 30/2/9
Input		Terminal and mounting	
Rated input voltage	230 Vac	Fixing method	Additional fixing by self-tapping screws
Rated frequency	50 - 60 Hz	Terminals	Pins for PCB
Output		Measures and weights Pin (a)	
Rated output voltage	2 x 9 Vac	Pin (ø)	0.8 mm
Rated Power	30 VA	Core type	El 60/30,5
No-load voltage (app. x factor)	1.11	.⊖ Weight	0.78 kg
No-load loss (typ.)	2.50 W	le l	
Efficiency	84.0 %	Core type Weight 40.0	
Standards		32.5	
Classification	Safety isolating transformer	2.	5
Approvals		A	• •
Approvals	cURus, VDE	30.0	
Environment		52.5	10.0 64.0 55.0
Ambient temperature max.	40 °C	¥	5.0
Safety and protection		54.0	3.5
Туре	Encapsulated	17 04.0	
Insulation class	VDE=B, UL=class 105		
moditation oldoo			
Protection index	IP 00		
	IP 00		
Protection index	IP 00 II non-short-circuit proof		
Protection index Safety class (prepared)	II		

